



Computer Architecture
(CSC-3501)
Lecture 9
(14 Feb 2008)

Seung-Jong Park (Jay)
<http://www.csc.lsu.edu/~sjpark>

1

CSC3501 - S.J. Park

3A.1 Introduction

- In 1953, Maurice Karnaugh was a telecommunications engineer at Bell Labs.
- While exploring the new field of digital logic and its application to the design of telephone circuits, he invented a graphical way of visualizing and then simplifying Boolean expressions.
- This graphical representation, now known as a Karnaugh map, or Kmap, is named in his honor.

4

CSC3501 - S.J. Park

Announcement

2

CSC3501 - S.J. Park

3A.2 Description of Kmaps and Terminology

- A Kmap is a matrix consisting of rows and columns that represent the output values of a Boolean function.
- The output values placed in each cell are derived from the minterms of a Boolean function.
- A *minterm* is a product term that contains all of the function's variables exactly once, either complemented or not complemented.

5

CSC3501 - S.J. Park

3A.1 Introduction

- Simplification of Boolean functions leads to simpler (and usually faster) digital circuits.
- Simplifying Boolean functions using identities is time-consuming and error-prone.
- This special section presents an easy, systematic method for reducing Boolean expressions.

3

CSC3501 - S.J. Park

3A.2 Description of Kmaps and Terminology

- For example, the minterms for a function having the inputs x and y are: $\bar{x}\bar{y}$, $\bar{x}y$, $x\bar{y}$, and xy
- Consider the Boolean function, $F(x, y) = xy + \bar{x}\bar{y}$
- Its minterms are:

Minterm	X	Y
$\bar{x}\bar{y}$	0	0
$\bar{x}y$	0	1
$x\bar{y}$	1	0
xy	1	1

6

CSC3501 – S.J. Park

3A.2 Description of Kmaps and Terminology

- Similarly, a function having three inputs, has the minterms that are shown in this diagram.

Minterm	X	Y	Z
$\bar{x}\bar{y}\bar{z}$	0	0	0
$\bar{x}\bar{y}z$	0	0	1
$\bar{x}y\bar{z}$	0	1	0
$\bar{x}yz$	0	1	1
$x\bar{y}\bar{z}$	1	0	0
$x\bar{y}z$	1	0	1
$xy\bar{z}$	1	1	0
xyz	1	1	1

7

CSC3501 – S.J. Park

3A.3 Kmap Simplification for Two Variables

- Of course, the minterm function that we derived from our Kmap was not in simplest terms.
 - That's what we started with in this example.
- We can, however, reduce our complicated expression to its simplest terms by finding adjacent 1s in the Kmap that can be collected into groups that are powers of two.
- In our example, we have two such groups.
 - Can you find them?

X	Y	0	1
0	0	0	1
1	1	1	1

10

CSC3501 – S.J. Park

3A.2 Description of Kmaps and Terminology

- A Kmap has a cell for each minterm.
- This means that it has a cell for each line for the truth table of a function.
- The truth table for the function $F(x,y) = xy$ is shown at the right along with its corresponding Kmap.

X	Y	XY
0	0	0
0	1	0
1	0	0
1	1	1

X	Y	0	1
0	0	0	0
1	0	0	1

8

CSC3501 – S.J. Park

3A.3 Kmap Simplification for Two Variables

- The best way of selecting two groups of 1s for our simple Kmap is shown below.
- We see that both groups are powers of two and that the groups overlap.
- The next slide gives guidance for selecting Kmap groups.

X	Y	0	1
0	0	0	1
1	1	1	1

11

CSC3501 – S.J. Park

3A.2 Description of Kmaps and Terminology

- As another example, we give the truth table and KMap for the function, $F(x,y) = x + y$ at the right.
- This function is equivalent to the OR of all of the minterms that have a value of 1. Thus:

$$F(x, y) = X + Y = \bar{x}y + x\bar{y} + xy$$

X	Y	X+Y
0	0	0
0	1	1
1	0	1
1	1	1

X	Y	0	1
0	0	0	1
1	1	1	1

9

CSC3501 – S.J. Park

3A.3 Kmap Simplification for Two Variables

The rules of Kmap simplification are:

- Groupings can contain only 1s; no 0s.
- Groups can be formed only at right angles; diagonal groups are not allowed.
- The number of 1s in a group must be a power of 2 – even if it contains a single 1.
- The groups must be made as large as possible.
- Groups can overlap and wrap around the sides of the Kmap.

12

CSC3501 – S.J. Park

3A.4 Kmap Simplification for Three Variables

- A Kmap for three variables is constructed as shown in the diagram below.
- We have placed each minterm in the cell that will hold its value.
 - Notice that the values for the yz combination at the top of the matrix form a pattern that is not a normal binary sequence.

X \ YZ	00	01	11	10
0	$\bar{x}\bar{y}\bar{z}$	$\bar{x}\bar{y}z$	$\bar{x}yz$	$\bar{x}y\bar{z}$
1	$x\bar{y}\bar{z}$	$x\bar{y}z$	xyz	$xy\bar{z}$

13

CSC3501 – S.J. Park

3A.4 Kmap Simplification for Three Variables

- This grouping tells us that changes in the variables x and y have no influence upon the value of the function: They are irrelevant.
- This means that the function,

$$F(X, Y, Z) = \bar{x}\bar{y}z + \bar{x}yz + x\bar{y}z + xyz$$
 reduces to $f(x,y) = z$.

You could verify this reduction with identities or a truth table.

X \ YZ	00	01	11	10
0	0	1	1	0
1	0	1	1	0

16

CSC3501 – S.J. Park

3A.4 Kmap Simplification for Three Variables

- Thus, the first row of the Kmap contains all minterms where x has a value of zero.
- The first column contains all minterms where y and z both have a value of zero.

X \ YZ	00	01	11	10
0	$\bar{x}\bar{y}\bar{z}$	$\bar{x}\bar{y}z$	$\bar{x}yz$	$\bar{x}y\bar{z}$
1	$x\bar{y}\bar{z}$	$x\bar{y}z$	xyz	$xy\bar{z}$

14

CSC3501 – S.J. Park

3A.4 Kmap Simplification for Three Variables

- Now for a more complicated Kmap. Consider the function:

$$F(X, Y, Z) = \bar{x}\bar{y}\bar{z} + \bar{x}\bar{y}z + \bar{x}yz + \bar{x}y\bar{z} + x\bar{y}\bar{z} + xy\bar{z}$$
- Its Kmap is shown below. There are (only) two groupings of 1s.
 - Can you find them?

X \ YZ	00	01	11	10
0	1	1	1	1
1	1	0	0	1

17

CSC3501 – S.J. Park

3A.4 Kmap Simplification for Three Variables

- Consider the function:

$$F(X, Y, Z) = \bar{x}\bar{y}z + \bar{x}yz + x\bar{y}z + xyz$$
- Its Kmap is given below.
 - What is the largest group of 1s that is a power of 2?

X \ YZ	00	01	11	10
0	0	1	1	0
1	0	1	1	0

15

CSC3501 – S.J. Park

3A.4 Kmap Simplification for Three Variables

- In this Kmap, we see an example of a group that wraps around the sides of a Kmap.
- This group tells us that the values of x and y are not relevant to the term of the function that is encompassed by the group.
 - What does this tell us about this term of the function?

What about the green group in the top row?

X \ YZ	00	01	11	10
0	1	1	1	1
1	1	0	0	1

18

CSC3501 - S.J. Park

3A.4 Kmap Simplification for Three Variables

- The green group in the top row tells us that only the value of x is significant in that group.
- We see that it is complemented in that row, so the other term of the reduced function is \bar{x}
- Our reduced function is: $F(x, y, z) = \bar{x} + \bar{y}$

Recall that we had six minterms in our original function!

x	yz	00	01	11	10
0		1	1	1	1
1		1	0	0	1

19

CSC3501 - S.J. Park

3A.5 Kmap Simplification for Four Variables

- Our three groups consist of:
 - A purple group entirely within the Kmap at the right.
 - A pink group that wraps the top and bottom.
 - A green group that spans the corners.
- Thus we have three terms in our final function:

$F(W, X, Y, Z) = \bar{x}\bar{y} + \bar{x}\bar{z} + \bar{w}yz$

WX	YZ	00	01	11	10
00		1	1		1
01					1
11			1		
10		1			1

22

CSC3501 - S.J. Park

3A.5 Kmap Simplification for Four Variables

- Our model can be extended to accommodate the 16 minterms that are produced by a four-input function.
- This is the format for a 16-minterm Kmap.

WX	YZ	00	01	11	10
00		$\bar{w}\bar{x}\bar{y}\bar{z}$	$\bar{w}\bar{x}\bar{y}z$	$\bar{w}\bar{x}y\bar{z}$	$\bar{w}\bar{x}yz$
01		$\bar{w}x\bar{y}\bar{z}$	$\bar{w}x\bar{y}z$	$\bar{w}xy\bar{z}$	$\bar{w}xyz$
11		$w\bar{x}\bar{y}\bar{z}$	$w\bar{x}\bar{y}z$	$wx\bar{y}\bar{z}$	$wx\bar{y}z$
10		$w\bar{x}y\bar{z}$	$w\bar{x}yz$	$wxy\bar{z}$	$wxyz$

20

CSC3501 - S.J. Park

3A.5 Kmap Simplification for Four Variables

- It is possible to have a choice as to how to pick groups within a Kmap, while keeping the groups as large as possible.
- The (different) functions that result from the groupings below are logically equivalent.

WX	YZ	00	01	11	10
00		1		1	
01		1			1
11			1		
10		1			1

WX	YZ	00	01	11	10
00		1			1
01		1			
11			1		
10				1	1

23

CSC3501 - S.J. Park

3A.5 Kmap Simplification for Four Variables

- We have populated the Kmap shown below with the nonzero minterms from the function:

$F(W, X, Y, Z) = \bar{w}\bar{x}\bar{y}\bar{z} + \bar{w}\bar{x}\bar{y}z + \bar{w}\bar{x}y\bar{z}$

Can you identify (only) three groups in this Kmap?

Recall that groups can overlap

WX	YZ	00	01	11	10
00		1	1		1
01					1
11					
10		1	1		1

21

CSC3501 - S.J. Park

3A.6 Don't Care Conditions

- Real circuits don't always need to have an output defined for every possible input.
 - For example, some calculator displays consist of 7-segment LEDs. These LEDs can display $2^7 - 1$ patterns, but only ten of them are useful.
- If a circuit is designed so that a particular set of inputs can never happen, we call this set of inputs a *don't care* condition.
- They are very helpful to us in Kmap circuit simplification.

24

CSC3501 – S.J. Park

3A.6 Don't Care Conditions

- In a Kmap, a don't care condition is identified by an X in the cell of the minterm(s) for the don't care inputs, as shown below.
- In performing the simplification, we are free to include or ignore the X's when creating our groups.

WX \ YZ	00	01	11	10
00	X	1	1	X
01		X	1	
11	X		1	
10			1	

25

CSC3501 – S.J. Park

3A.6 Don't Care Conditions

- The truth table of:

$$F(W, X, Y, Z) = \bar{W}\bar{X} + YZ$$
is different from the truth table of:

$$F(W, X, Y, Z) = \bar{W}Z + YZ$$
- However, the values for which they differ, are the inputs for which we have don't care conditions.

WX \ YZ	00	01	11	10
00	X	1	1	X
01		X	1	
11	X		1	
10			1	

WX \ YZ	00	01	11	10
00	X	1	1	X
01		X	1	
11	X		1	
10			1	

28

CSC3501 – S.J. Park

3A.6 Don't Care Conditions

- In one grouping in the Kmap below, we have the function:

$$F(W, X, Y, Z) = \bar{W}\bar{X} + YZ$$

WX \ YZ	00	01	11	10
00	X	1	1	X
01		X	1	
11	X		1	
10			1	

26

CSC3501 – S.J. Park

3A Conclusion

- Kmaps provide an easy graphical method of simplifying Boolean expressions.
- A Kmap is a matrix consisting of the outputs of the minterms of a Boolean function.
- In this section, we have discussed 2- 3- and 4-input Kmaps. This method can be extended to any number of inputs through the use of multiple tables.

29

CSC3501 – S.J. Park

3A.6 Don't Care Conditions

- A different grouping gives us the function:

$$F(W, X, Y, Z) = \bar{W}Z + YZ$$

WX \ YZ	00	01	11	10
00	X	1	1	X
01		X	1	
11	X		1	
10			1	

27

CSC3501 – S.J. Park

3A Conclusion

Recapping the rules of Kmap simplification:

- Groupings can contain only 1s; no 0s.
- Groups can be formed only at right angles; diagonal groups are not allowed.
- The number of 1s in a group must be a power of 2 – even if it contains a single 1.
- The groups must be made as large as possible.
- Groups can overlap and wrap around the sides of the Kmap.
- Use don't care conditions when you can.

30